KEMET Part Number: C1206X223JAGACAUTO



SMD Auto C0G Flex, Ceramic, 0.022 uF, 5%, 250 VDC, C0G, SMD, MLCC, FT-CAP, Ultra-Stable, Automotive Grade, 1206



| Dimensions | |
|------------|-----------------|
| Chip Size | 1206 |
| L | 3.3mm +/-0.4mm |
| W | 1.6mm +/-0.35mm |
| Т | 1.6mm +/-0.20mm |
| В | 0.6mm +/-0.25mm |

| Packaging Specifications | | |
|--------------------------|--------------------------|--|
| Packaging: | T&R, 180mm, Plastic Tape | |
| Packaging Quantity: | 2000 | |

| General Information | |
|---------------------|---|
| Series: | SMD Auto C0G Flex |
| Style: | SMD Chip |
| Description: | SMD, MLCC, FT-CAP, Ultra- Stable, Automotive Grade |
| Features: | FT-CAP, Ultra-Stable, Automotive Grade |
| RoHS: | Yes |
| Termination: | Flexible Termination |
| Marking: | No |
| Qualifications: | AEC-Q200 |
| AEC-Q200: | Yes |
| Component Weight: | 36 mg |
| Shelf Life: | 78 Weeks |
| MSL: | 1 |

| Specifications | | |
|---|------------------------|--|
| Capacitance: | 0.022 uF | |
| Measurement Condition: | 1 kHz 1.0Vrms | |
| Capacitance Tolerance: | 5% | |
| Voltage DC: | 250 VDC | |
| Dielectric Withstanding Voltage: | 625 VDC | |
| Temperature Range: | -55/+125°C | |
| Temperature Coefficient: | COG | |
| Capacitance Change with Reference to +25°C and 0 VDC Applied (TCC): | 30 ppm/C, 1kHz 1.0Vrms | |
| Dissipation Factor: | 0.1% 1 kHz 1.0Vrms | |
| Aging Rate: | 0% Loss/Decade Hour | |
| Insulation Resistance: | 45.4545 GOhms | |

Statements of suitability for certain applications are based on our knowledge of typical operating conditions for such applications, but are not intended to constitute - and we specifically disclaim - any warranty concerning suitability for a specific customer application or use. This Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by us with reference to the use of our products is given gratis, and we assume no obligation or liability for the advice given or results obtained.

