**DC Line Filters** 

# Common Mode for Signal Line, SMD Type, SPF Series



#### **Overview**

The KEMET SPF coils are common mode chokes with a wide variety of characteristics. These SMD toroidal coils are designed with our proprietary ferrite cores and are suitable for noise countermeasure in DC signal line circuits.

## **Applications**

· Base station

## **Benefits**

- · Proprietary S15H ferrite material
- High L due to ferrite material
- · High current due to our unique design
- Withstanding voltage: 600 VDC (one minute, between lines)
- Insulation resistance: more than 10 M $\Omega$  (250 VDC, between lines)
- SMD
- Operating temperature range from -40°C to +120°C
- UL94 V-0 flame retardant rated cap
- · RoHS Compliant




## **Part Number System**

SPF-	100-	1R1A	010
Series	Rated Current (A)	Wire Diameter (mm)	Inductance Code (mH)
SPF-	100 = 10 A	R = Decimal point  Example:	010 = 1.0 mH
		1R1A = 1.1 mm	

DC Line Filters - Common Mode for Signal Line, SMD Type, SPF Series



## **Dimensions - Millimeters**



## **Environmental Compliance**

All KEMET DC line filters are RoHS Compliant.



## **Performance Characteristics**

ltem	Performance Characteristics
Rated Voltage	150 VDC
Withstanding Voltage	600 VDC (1 minute, between lines)
Insulation Resistance	> 10 MΩ at 250 VDC (between lines)
Rated Current	10 A
Rated Inductance	1 mH minimum
Inductance Measurement Condition	10 kHz
Rated DC Resistance	12 mΩ maximum
Operating Temperature	-40°C to +120°C (not including self-temperature rise)






## **Table 1 - Ratings & Part Number Reference**

Part	Rated Voltage	Rated Current	Inductance (mH)	DC Resistance/Line (mΩ) Maximum	Weight
Number	DC (V)	DC (A)	Minimum		(g)
SPF-100-1R1A010	150	10	1	10	26

## **Frequency Characteristics**



## **Packaging**


Part Type	Packaging Type	Pieces per Package	Pieces per Box
SPF-100-1R1A010	Tray	35	210

DC Line Filters - Common Mode for Signal Line, SMD Type, SPF Series



## **Soldering Process**

## **Recommended Reflow Soldering Profile:**



### Reference ICP/JEDEC J-STD-020E

Profile Feature	Pb-Free Assembly	
Preheat/Soak		
Temperature Minimum (T <sub>Smin</sub> )	150°C	
Temperature Maximum (T <sub>smax</sub> )	180°C	
Time $(t_s)$ from $T_{smin}$ to $T_{smax}$ )	80 - 120 seconds	
Ramp-up Rate $(T_L \text{ to } T_P)$	3°C/second maximum	
Liquidous Temperature $(T_L)$	230°C	
Time Above Liquidous (t <sub>L</sub> )	30 – 40 seconds	
Peak Temperature (T <sub>P</sub> )	250°C	
Time within 5°C of Maximum Peak Temperature (t <sub>P</sub> )	5 seconds maximum	
Ramp-down Rate $(T_p \text{ to } T_L)$	6°C/second maximum	
Time 25°C to Peak Temperature	8 minutes maximum	

KEVET a YAGEO company

DC Line Filters - Common Mode for Signal Line, SMD Type, SPF Series

## **Handling Precautions**

## **Precautions for product storage**

DC Line Filters should be stored in normal working environments. While the chokes themselves are quite robust in other environments, solderability will be degraded by exposure to high temperatures, high humidity, corrosive atmospheres, and long term storage.

KEMET recommends that maximum storage temperature not exceed 40°C and maximum storage humidity not exceed 70% relative humidity. Atmospheres should be free of chlorine and sulfur bearing compounds. Temperature fluctuations should be minimized to avoid condensation on the parts. Do not store near strong magnetic fields, as this might magnetize the product.

For optimized solderability, DC line filter stock should be used promptly, preferably within six months of receipt.

## **Product temperature rise values**

The values listed for temperature rise are the result of self-heating in wires when the rated current (commercial frequency) is applied. When using, check and evaluate the value of the core temperature rise under actual operating conditions.



DC Line Filters - Common Mode for Signal Line, SMD Type, SPF Series

## **KEMET Electronics Corporation Sales Offices**

For a complete list of our global sales offices, please visit www.kemet.com/sales.

### **Disclaimer**

All product specifications, statements, information and data (collectively, the "Information") in this datasheet are subject to change. The customer is responsible for checking and verifying the extent to which the Information contained in this publication is applicable to an order at the time the order is placed. All Information given herein is believed to be accurate and reliable, but it is presented without guarantee, warranty, or responsibility of any kind, expressed or implied.

Statements of suitability for certain applications are based on KEMET Electronics Corporation's ("KEMET") knowledge of typical operating conditions for such applications, but are not intended to constitute – and KEMET specifically disclaims – any warranty concerning suitability for a specific customer application or use. The Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by KEMET with reference to the use of KEMET's products is given gratis, and KEMET assumes no obligation or liability for the advice given or results obtained.

Although KEMET designs and manufactures its products to the most stringent quality and safety standards, given the current state of the art, isolated component failures may still occur. Accordingly, customer applications which require a high degree of reliability or safety should employ suitable designs or other safeguards (such as installation of protective circuitry or redundancies) in order to ensure that the failure of an electrical component does not result in a risk of personal injury or property damage.

Although all product-related warnings, cautions and notes must be observed, the customer should not assume that all safety measures are indicted or that other measures may not be required.

When providing KEMET products and technologies contained herein to other countries, the customer must abide by the procedures and provisions stipulated in all applicable export laws and regulations, including without limitation the International Traffic in Arms Regulations (ITAR), the US Export Administration Regulations (EAR) and the Japan Foreign Exchange and Foreign Trade Act.