

## **Features**

- Surface Mount SMC package
- Standoff Voltage: 12 to 58 volts
- Power Dissipation: 3000 watts
- RoHS compliant\*
- AEC-Q101 compliant\*\*
- Typical temperature coefficient:  $\Delta V_{BR} = 0.1$  % x V<sub>BR</sub> @ 25 °C x  $\Delta T$

## **Applications**

- Protection of power buses
- Protection of I/O interfaces
- Overvoltage transient protection
- Entertainment applications
- Comfort applications
- Telecom, computer, industrial and consumer electronics applications

# SMLJ-Q Transient Voltage Suppressor Diode Series

#### **General Information**

Bourns offers Transient Voltage Suppressor Diodes for surge and ESD protection applications, in compact chip package DO-214AB (SMC) size format. The Transient Voltage Suppressor series offers a choice of Working Peak Reverse Voltage from 12 V up to 58 V. Typical fast response times are less than 1.0 picosecond from 0 V to Breakdown Voltage.

Bourns® Chip Diodes conform to JEDEC standards, are easy to handle with standard pick and place equipment and the flat configuration minimizes roll away.

#### **Additional Information**

Click these links for more information:



### **Agency Recognition**

Description					
UL	File Number: E153537				

### Electrical Characteristics (@ T<sub>A</sub> = 25 °C Unless Otherwise Noted)

Parameter	Symbol	Value	Unit
Minimum Peak Pulse Power Dissipation ( $T_P = 1 \text{ ms}$ ) (Note 1,2)	P <sub>PK</sub>	3000	Watts
Peak Forward Surge Current 8.3 ms Single Half Sine Wave Superimposed on Rated Load (JEDEC Method) <sup>(Note 3)</sup>	I <sub>FSM</sub>	300	Amps
Operating Temperature Range	TJ	-55 to +150	°C
Storage Temperature Range	T <sub>STG</sub>	-55 to +150	°C

1. Non-repetitive current pulse, per Pulse Waveform graph and derated above T<sub>A</sub> = 25 °C per Pulse Derating Curve.

2. Mounted on 5.0 mm<sup>2</sup> (0.03 mm thick) copper pads to each terminal.

3. 8.3 ms Single Sine Wave duty cycle = 4 pulses maximum per minute (unidirectional units only).



**Asia-Pacific:** Tel: +886-2 2562-4117 · Email: asiacus@bourns.com Europe: Tel: +36 88 885 877 · Email: eurocus@bourns.com The Americas: Tel: +1-951 781-5500 · Email: americus@bourns.com www.bourns.com



\*RoHS Directive 2015/863, Mar 31, 2015 and Annex.

\*\*"Q" part number suffix indicates AEC-Q101 compliance.

Specifications are subject to change without notice.

Users should verify actual device performance in their specific applications.

The products described herein and this document are subject to specific legal disclaimers as set forth on the last page of this document, and at www.bourns.com/docs/legal/disclaimer.pdf.

# BOURNS

Unidirectional De- vice Bidirectional Device		Breakdown Voltage V <sub>BR</sub> (Volts)		Working Peak Reverse Voltage	Maximum Reverse Leakage @ V <sub>RWM</sub>	Maximum Clamping Voltage @ I <sub>pp</sub> (10/1000 µs)	Maximum Peak Pulse Current (10/1000 μs)	Maximum Clamping Voltage @ I <sub>pp</sub> (8/20 µs)	Maximum Peak Pulse Current (8/20 µs)			
Part Number	Part Marking	Part Number	Part Marking	Min.	Max.	@ I <sub>T</sub> (mA)	V <sub>RWM</sub> (Volts)	Ι <sub>R</sub> (μΑ)	V <sub>c</sub> (V)	I <sub>рр</sub> (А)	V <sub>c</sub> (V)	I <sub>рр</sub> (А)
SMLJ12A-Q	HEEQ	SMLJ12CA-Q	IEEQ	13.3	14.7	1	12	2	19.9	150.60	25.90	754.00
SMLJ13A-Q	HEGQ	SMLJ13CA-Q	IEGQ	14.4	15.9	1	13	2	21.5	139.40	28.00	697.50
SMLJ14A-Q	HEKQ	SMLJ14CA-Q	IEKQ	15.6	17.2	1	14	2	23.2	129.40	30.20	646.50
SMLJ15A-Q	HEMQ	SMLJ15CA-Q	IEMQ	16.7	18.5	1	15	2	24.4	123.00	31.70	615.00
SMLJ16A-Q	HEPQ	SMLJ16CA-Q	IEPQ	17.8	19.7	1	16	2	26.0	115.40	33.80	577.00
SMLJ17A-Q	HERQ	SMLJ17CA-Q	IERQ	18.9	20.9	1	17	2	27.6	106.60	35.90	543.50
SMLJ18A-Q	HETQ	SMLJ18CA-Q	IETQ	20.0	22.1	1	18	2	29.2	102.80	38.00	513.50
SMLJ20A-Q	HEVQ	SMLJ20CA-Q	IEVQ	22.2	24.5	1	20	2	32.4	92.60	42.10	463.00
SMLJ22A-Q	HEXQ	SMLJ22CA-Q	IEXQ	24.4	26.9	1	22	2	35.5	84.40	46.20	422.50
SMLJ24A-Q	HEZQ	SMLJ24CA-Q	IEZQ	26.7	29.5	1	24	2	38.9	77.20	50.60	385.50
SMLJ26A-Q	HFEQ	SMLJ26CA-Q	IFEQ	28.9	31.9	1	26	2	42.1	71.20	54.70	356.50
SMLJ28A-Q	HFGQ	SMLJ28CA-Q	IFGQ	31.1	34.4	1	28	2	45.4	66.00	59.00	330.50
SMLJ30A-Q	HFKQ	SMLJ30CA-Q	IFKQ	33.3	36.8	1	30	2	48.4	62.00	62.90	310.00
SMLJ33A-Q	HFMQ	SMLJ33CA-Q	IFMQ	36.7	40.6	1	33	2	53.3	56.20	69.30	281.50
SMLJ36A-Q	HFPQ	SMLJ36CA-Q	IFPQ	40.0	44.2	1	36	2	58.1	51.60	75.50	258.00
SMLJ40A-Q	HFRQ	SMLJ40CA-Q	IFRQ	44.4	49.1	1	40	2	64.5	46.40	83.90	232.50
SMLJ43A-Q	HFTQ	SMLJ43CA-Q	IFTQ	47.8	52.8	1	43	2	69.4	43.20	90.20	216.00
SMLJ45A-Q	HFVQ	SMLJ45CA-Q	IFVQ	50.0	55.3	1	45	2	72.7	41.20	94.50	206.50
SMLJ48A-Q	HFXQ	SMLJ48CA-Q	IFXQ	53.3	58.9	1	48	2	77.4	38.80	100.60	194.00
SMLJ51A-Q	HFZQ	SMLJ51CA-Q	IFZQ	56.7	62.7	1	51	2	82.4	36.40	107.10	182.00
SMLJ54A-Q	HGEQ	SMLJ54CA-Q	IGEQ	60.0	66.3	1	54	2	87.1	34.40	113.20	172.00
SMLJ58A-Q	HGGQ	SMLJ58CA-Q	IGGQ	64.4	71.2	1	58	2	93.6	32.00	121.70	160.50

## Electrical Characteristics (@ T<sub>A</sub> = 25 °C Unless Otherwise Noted)

Notes:

1. Suffix 'A' denotes a 5 % tolerance unidirectional device.

2. Suffix 'CA' denotes a 5 % tolerance bidirectional device.


Specifications are subject to change without notice. Users should verify actual device performance in their specific applications. The products described herein and this document are subject to specific legal disclaimers as set forth on the last page of this document, and at <u>www.bourns.com/docs/legal/disclaimer.pdf</u>.

# BOURNS

100

1000

#### **Performance Graphs**



Specifications are subject to change without notice.

1.0 µs

0.1

0.1 µs

Shown in Pulse Waveform Graph

Users should verify actual device performance in their specific applications.

10 µs

100 µs

TP - Pulse Width

1.0 ms

10 ms

The products described herein and this document are subject to specific legal disclaimers as set forth on the last page of this document, and at www.bourns.com/docs/legal/disclaimer.pdf.

0.5

0.0

0

25

50

75


T<sub>L</sub> - Lead Temperature (°C)

100

125

150


# BOURNS




А	<u>6.60 - 7.11</u> (0.260 - 0.280)		
В	<u>5.59 - 6.22</u> (0.220 - 0.245)		
С	<u>2.90 - 3.20</u> (0.114 - 0.126)		
D	<u>0.15 - 0.31</u> (0.006 - 0.012)		
E	<u>7.75 - 8.13</u> (0.305 - 0.320)		
F	<u>0.203</u> (0.008) MAX.		
G	<u>2.00 - 2.62</u> (0.079 - 0.103)		
Н	<u>0.76 - 1.52</u> (0.030 - 0.060)		




### **Typical Part Marking**



**Recommended Footprint** 





Dimension	SMC (DO-214AB)
a (Marc)	4.69
a (Max.)	(0.185)
b (Min.)	3.07
	(0.121)
c (Min.)	1.52
	(0.060)

DIMENSIONS:  $\frac{MM}{(INCHES)}$ 

## **Physical Specifications**

Case	
Polarity	Cathode band indicates unidirectional device
	No cathode band indicates bidirectional device

### How to Order

Deles	SMLJ	12 	CA - Q
Package SMLJ = SMC/DO-214AB			
Working Peak Reverse Voltage			
Suffix A = 5 % Tolerance Unidirectional Device CA = 5 % Tolerance Bidirectional Device			
AEC-Q101 Suffix — Q = AEC-Q101 Compliant, 13-inch Reel QH = AEC-Q101 Compliant, 7-inch Reel			]

### **Environmental Specifications**

Moisture Sensitivity Level	1
ESD Classification (HBM)	В

Specifications are subject to change without notice.


Users should verify actual device performance in their specific applications.


The products described herein and this document are subject to specific legal disclaimers as set forth on the last page of this document, and at www.bourns.com/docs/legal/disclaimer.pdf.

# BOURNS


#### **Packaging Information**

The product will be dispensed in tape and reel format (see diagram below).





Direction of Feed



		SMC (DO-214AB)				
Item	Symbol	7-Inch Reel	13-Inch Reel			
Carrier Width	A	$\frac{6.0 \pm 2.0}{(0.236 - 0.079)}$				
Carrier Length	В		± 0.20 ± 0.008)			
Carrier Depth	С		: 0.20 ± 0.008)			
Sprocket Hole	d		± 0.10 ± 0.004)			
Reel Outside Diameter	D	<u>178</u> (7.008)	<u>330</u> (12.992)			
Reel Inner Diameter	D <sub>1</sub>	<u>50.0</u> (1.969) MIN.				
Feed Hole Diameter	D <sub>2</sub>	<u>13.0 +0.50/-0.20</u> (0.512 +0.020/-0.008)				
Sprocket Hole Position	E		± 0.10 ± 0.004)			
Punch Hole Position	F	$\frac{7.50 \pm 0.10}{(0.295 \pm 0.004)}$				
Punch Hole Pitch	Р		<u>± 0.10</u> ± 0.004)			
Sprocket Hole Pitch	P <sub>0</sub>	$\frac{4.00 \pm 0.10}{(0.157 \pm 0.004)}$				
Embossment Center	P <sub>1</sub>	$\frac{2.00 \pm 0.10}{(0.079 \pm 0.004)}$				
Overall Tape Thickness	Т	$\frac{0.30 \pm 0.10}{(0.012 \pm 0.004)}$				
Tape Width	w	$\frac{16.00 \pm 0.30}{(0.630 \pm 0.012)}$				
Reel Width	W <sub>1</sub>	<u>22.4</u> (0.882) MAX.				
Quantity per Reel		500	3000			

## REV. 02/21

Specifications are subject to change without notice.

Users should verify actual device performance in their specific applications.

The products described herein and this document are subject to specific legal disclaimers as set forth on the last page of this document, and at www.bourns.com/docs/legal/disclaimer.pdf.

# **Legal Disclaimer Notice**

This legal disclaimer applies to purchasers and users of Bourns<sup>®</sup> products manufactured by or on behalf of Bourns, Inc. and its affiliates (collectively, "Bourns").

Unless otherwise expressly indicated in writing, Bourns<sup>®</sup> products and data sheets relating thereto are subject to change without notice. Users should check for and obtain the latest relevant information and verify that such information is current and complete before placing orders for Bourns<sup>®</sup> products.

The characteristics and parameters of a Bourns<sup>®</sup> product set forth in its data sheet are based on laboratory conditions, and statements regarding the suitability of products for certain types of applications are based on Bourns' knowledge of typical requirements in generic applications. The characteristics and parameters of a Bourns<sup>®</sup> product in a user application may vary from the data sheet characteristics and parameters due to (i) the combination of the Bourns<sup>®</sup> product with other components in the user's application, or (ii) the environment of the user application itself. The characteristics and parameters of a Bourns<sup>®</sup> product also can and do vary in different applications and actual performance may vary over time. Users should always verify the actual performance of the Bourns<sup>®</sup> product in their specific devices and applications, and make their own independent judgments regarding the amount of additional test margin to design into their device or application to compensate for differences between laboratory and real world conditions.

Unless Bourns has explicitly designated an individual Bourns<sup>®</sup> product as meeting the requirements of a particular industry standard (e.g., ISO/TS 16949) or a particular qualification (e.g., UL listed or recognized), Bourns is not responsible for any failure of an individual Bourns<sup>®</sup> product to meet the requirements of such industry standard or particular qualification. Users of Bourns<sup>®</sup> products are responsible for ensuring compliance with safety-related requirements and standards applicable to their devices or applications.

Bourns<sup>®</sup> products are not recommended, authorized or intended for use in nuclear, lifesaving, life-critical or life-sustaining applications, nor in any other applications where failure or malfunction may result in personal injury, death, or severe property or environmental damage. Unless expressly and specifically approved in writing by two authorized Bourns representatives on a case-by-case basis, use of any Bourns<sup>®</sup> products in such unauthorized applications might not be safe and thus is at the user's sole risk. Life-critical applications include devices identified by the U.S. Food and Drug Administration as Class III devices and generally equivalent classifications outside of the United States.

Bourns expressly identifies those Bourns<sup>®</sup> standard products that are suitable for use in automotive applications on such products' data sheets in the section entitled "Applications." Unless expressly and specifically approved in writing by two authorized Bourns representatives on a case-by-case basis, use of any other Bourns<sup>®</sup> standard products in an automotive application might not be safe and thus is not recommended, authorized or intended and is at the user's sole risk. If Bourns expressly identifies a sub-category of automotive application in the data sheet for its standard products (such as infotainment or lighting), such identification means that Bourns has reviewed its standard product and has determined that if such Bourns<sup>®</sup> standard product is considered for potential use in automotive applications, it should only be used in such sub-category of automotive applications. Any reference to Bourns<sup>®</sup> standard product in the data sheet as compliant with the AEC-Q standard or "automotive grade" does not by itself mean that Bourns has approved such product for use in an automotive application.

Bourns<sup>®</sup> standard products are not tested to comply with United States Federal Aviation Administration standards generally or any other generally equivalent governmental organization standard applicable to products designed or manufactured for use in aircraft or space applications. Bourns expressly identifies Bourns<sup>®</sup> standard products that are suitable for use in aircraft or space applications on such products' data sheets in the section entitled "Applications." Unless expressly and specifically approved in writing by two authorized Bourns representatives on a case-by-case basis, use of any other Bourns<sup>®</sup> standard product in an aircraft or space application might not be safe and thus is not recommended, authorized or intended and is at the user's sole risk.

The use and level of testing applicable to Bourns<sup>®</sup> custom products shall be negotiated on a case-by-case basis by Bourns and the user for which such Bourns<sup>®</sup> custom products are specially designed. Absent a written agreement between Bourns and the user regarding the use and level of such testing, the above provisions applicable to Bourns<sup>®</sup> standard products shall also apply to such Bourns<sup>®</sup> custom products.

Users shall not sell, transfer, export or re-export any Bourns<sup>®</sup> products or technology for use in activities which involve the design, development, production, use or stockpiling of nuclear, chemical or biological weapons or missiles, nor shall they use Bourns<sup>®</sup> products or technology in any facility which engages in activities relating to such devices. The foregoing restrictions apply to all uses and applications that violate national or international prohibitions, including embargos or international regulations. Further, Bourns<sup>®</sup> products and Bourns technology and technical data may not under any circumstance be exported or re-exported to countries subject to international sanctions or embargoes. Bourns<sup>®</sup> products may not, without prior authorization from Bourns and/or the U.S. Government, be resold, transferred, or re-exported to any party not eligible to receive U.S. commodities, software, and technical data.

To the maximum extent permitted by applicable law, Bourns disclaims (i) any and all liability for special, punitive, consequential, incidental or indirect damages or lost revenues or lost profits, and (ii) any and all implied warranties, including implied warranties of fitness for particular purpose, non-infringement and merchantability.

For your convenience, copies of this Legal Disclaimer Notice with German, Spanish, Japanese, Traditional Chinese and Simplified Chinese bilingual versions are available at:

Web Page: <u>http://www.bourns.com/legal/disclaimers-terms-and-policies</u> PDF: <u>http://www.bourns.com/docs/Legal/disclaimer.pdf</u>